7. Electrical Parts List

Loc.No	Part No	Description ; Specification	Remark
601	**-**	**ASSY PCB-MAIN(VCR);**	
S.M.P.S. PARTS			
BD1S01	AC27-92001M	COIL-INDUCTOR;RH3.5X6.5RS,BEAD(RADIAL),-	
BD1SS2	AC27-92001M	COIL-INDUCTOR;RH3.5X6.5RS,BEAD(RADIAL),-	
BD1SS3	AC27-92001M	COIL-INDUCTOR;RH3.5X6.5RS,BEAD(RADIAL),-	
BD1SS4	AC27-92001M	COIL-INDUCTOR;RH3.5X6.5RS,BEAD(RADIAL),-	
C1SS01	2305-001021	C-FILM,MPEF;100nF,20%,275V,TP,17.5x7x13.	⚠
C1SS02	2305-001021	C-FILM,MPEF;100nF,20%,275V,TP,17.5x7x13.	⚠
C1SS03	2201-000828	C-CERAMIC,DISC;3.3nF,20%,400V,Y5U,TP,15x	⚠
C1SS04	2201-000828	C-CERAMIC,DISC;3.3nF,20%,400V,Y5U,TP,15x	⚠
C1SS05	2201-000129	C-CERAMIC,DISC;0.1nF,10%,1kV,Y5P,TP,7x4,	⚠
C1SS06	2201-000129	C-CERAMIC,DISC;0.1nF,10%,1kV,Y5P,TP,7x4,	⚠
C1SS10	2401-003302	C-AL;47uF,20%,400V,GP,TP,18X31.5,7.	DVD-V55K Only
	2401-001682	C-AL;82uF,20%,400V,GP,BK,22x25,10	Other Models
C1SS11	2305-001029	C-FILM,MPEF;10nF,10%,630V,TP,12x9x12.5,5	
C1SS12	2401-001186	C-AL;33uF,20%,35V,GP,TP,6.3x7,2.5	DVD-V85K/V72K Only
	2401-003046	C-AL;47uF,20%,50V,WT,TP,6.3x11,2.5	Other Models
C1SS13	2201-000376	C-CERAMIC,DISC;0.22nF,5%,50V,SL,TP,6.3x3	
C1SS14	2201-000129	C-CERAMIC,DISC;0.1nF,10%,1kV,Y5P,TP,7x4,	
C1SS15	2401-000118	C-AL;1000uF,20%,10V,GP,TP,10x12.5,5	
C1SS16	2401-000118	C-AL;1000uF,20%,10V,GP,TP,10x12.5,5	
C1SS17	2401-001992	C-AL;2200UF,20%,10V,WT,TP,10X20MM,5	
C1SS18	2401-000680	C-AL;2200uF,20%,10V,LZ,TP,12.5x25mm	
C1SS19	2401-000385	C-AL;10uF,20%,100V,GP,TP,6.3x11,5	
C1SS20	2201-000812	C-CERAMIC,DISC;2.2nF,20%,400V,Y5U,BK,12.	
C1SS21	2401-003477	C-AL;330UF,20%,25V,LZ,TP,10X12.5MM,	
C1SS22	2401-003477	C-AL;330UF,20%,25V,LZ,TP,10X12.5MM,	
C1SS23	2401-003137	C-AL;330UF,20%,50V,WT,TP,10X16MM,5	
C1SS24	2401-001479	C-AL;470uF,20%,10V,GP,TP,-,-	
C1SS25	2401-000118	C-AL;1000uF,20%,10V,GP,TP,10x12.5,5	
C1SS26	2401-003059	C-AL;1000UF,20%,16V,WT,TP,10X16,5	
C1SS27	2301-000129	C-FILM,PEF;100nF,5%,50V,TP,10X9X4.3X5,5m	
CN01	3708-000249	CONNECTOR-FPC/FFC/PIC;27P,1.25mm,STRAIGH	
CN1S01	3711-000178	CONNECTOR-HEADER;1WALL,2P,1R,3.96mm,STRA	
D1SS01	0402-001196	DIODE-RECTIFIER;1T5,600V,1A,TS-1,TP	
D1SS02	0402-001196	DIODE-RECTIFIER;1T5,600V,1A,TS-1,TP	
D1SS03	0402-001196	DIODE-RECTIFIER;1T5,600V,1A,TS-1,TP	
D1SS04	0402-001196	DIODE-RECTIFIER;1T5,600V,1A,TS-1,TP	
D1SS05	0402-001196	DIODE-RECTIFIER;1T5,600V,1A,TS-1,TP	
D1SS10	0402-001195	DIODE-RECTIFIER;F1T4,400V,1.0A,TS-1,TP	
D1SS11	0402-000012	DIODE-RECTIFIER;UF4007,1KV,1A,DO-41,TP	
D1SS12	0404-001097	DIODE-SCHOTTKY;SG45,45V,7500mA,TO-220A,B	
D1SS13	0404-001097	DIODE-SCHOTTKY;SG45,45V,7500mA,TO-220A,B	
D1SS14	0404-001097	DIODE-SCHOTTKY;SG45,45V,7500mA,TO-220A,B	
D1SS15	0402-001195	DIODE-RECTIFIER;F1T4,400V,1.0A,TS-1,TP	
D1SS16	0402-001194	DIODE-RECTIFIER;UG2D,200V,2A,DO-204AC,TP	
D1SS17	0402-001195	DIODE-RECTIFIER;F1T4,400V,1.0A,TS-1,TP	
D1SS18	0402-001195	DIODE-RECTIFIER;F1T4,400V,1.0A,TS-1,TP	
D1SS19	0402-001195	DIODE-RECTIFIER;F1T4,400V,1.0A,TS-1,TP	
F1SS01	3601-001123	FUSE-CARTRIDGE;250V,1.6A,TIME-LAG,CERAMI	⚠
IC1S01	1203-001803	IC-PWM CONTROLLER;STR-F6552,TO-220,5P;-,	
IC1S02	0604-000186	PHOTO-COUPLER;TR,-,200mW,DIP-4,ST	⚠
IC1S03	AC14-12006D	IC;KA431Z,TO-92,TAPING	
L1SS01	AC29-00002A	FILTER LINE NOISE;-,30mH,-,-,BLF-2116	⚠
L1SS02	AC29-30050B	FILTER-LINE NOISE;-,400uH,-,AC250V,TR12.	⚠
L1SS03	AC27-12001N	COIL-CHOKE;10UH-15%,RA,K-30,Q80,150KHZ,-	
L1SS04	AC27-12001N	COIL-CHOKE;10UH-15%,RA,K-30,Q80,150KHZ,-	
L1SS05	AC27-12001N	COIL-CHOKE;10UH-15%,RA,K-30,Q80,150KHZ,-	
PT1S01	AC26-00001S	TRANS SWITCHING;EER3530,COMBO3,-,100~240	⚠
R1SS10	2006-000262	R-CEMENT;2.7ohm,10%,2W,CB,TP,7.5x11x20.	
R1SS11	2001-000113	R-CARBON;18KOHM,5%,1/4W,AA,TP,2.4X6.4MM	
R1SS12	2001-000113	R-CARBON;18KOHM,5%,1/4W,AA,TP,2.4X6.4MM	
R1SS13	2001-000113	R-CARBON;18KOHM,5%,1/4W,AA,TP,2.4X6.4MM	
R1SS14	2001-000113	R-CARBON;18KOHM,5%,1/4W,AA,TP,2.4X6.4MM	
R1SS15	2001-000096	R-CARBON(S);1MOHM,5%,1/2W,AA,TP,2.4X6.4M	
R1SS16	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R1SS17	2001-000793	R-CARBON;47OHM,5%,1/8W,AA,TP,1.8X3.2MM	DVD-V85K/V72K Only
	2001-000568	R-CARBON;27OHM,5%,1/8W,AA,TP,1.8X3.2MM	Other Models
R1SS18	2006-000273	R-CEMENT;27KOHM,5%,2W,CA,BK,6.4X6.5X18M	
R1SS19	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SS20	2003-000105	R-METAL OXIDE;0.33ohm,5%,2W,AD,TP,6x16mm	
R1SS21	2006-000273	R-CEMENT;27KOHM,5%,2W,CA,BK,6.4X6.5X18M	
R1SS31	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SS32	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SS33	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SS34	2004-000869	R-METAL;3Kohm,1%,1/8W,AA,TP,1.8x3.2mm	
R1SS35	2004-000459	R-METAL;2.2Kohm,1%,1/8W,AA,TP,1.8x3.2m	
R1SS36	2003-000471	R-METAL OXIDE(S);10ohm,5%,2W,AA,TP,4x12m	
POWER DRIVE PARTS			
C1P01A	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C1P102	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C1P103	2401-000463	C-AL;10uF,20%,35V,GP,-,5x5,2mm	
C1P104	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C1P105	2401-003059	C-AL;1000UF,20%,16V,WT,TP,10X16,5	
C1P106	2401-000463	C-AL;10uF,20%,35V,GP,-,5x5,2mm	
C1P107	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C1P109	2401-000463	C-AL;10uF,20%,35V,GP,-,5x5,2mm	
C1P110	2401-000463	C-AL;10uF,20%,35V,GP,-,5x5,2mm	
C1P111	2401-000463	C-AL;10uF,20%,35V,GP,-,5x5,2mm	
C1P112	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C1P113	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C1P114	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C1P115	2401-000463	C-AL;10uF,20%,35V,GP,-,5x5,2mm	
C1P116	2401-003122	C-AL;4.7uF,20%,50V,LL,TP,4X7,1.5	
D1P103	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
D1P104	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
D1P105	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
D1P107	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
D1P108	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
Q1P101	0501-000616	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1W,TO-92L	
Q1P102	0504-000142	TR-DIGITAL;KSR2001,PNP,300MW,4.7K/4.7K,T	
Q1P103	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
Q1P104	0501-000616	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1W,TO-92L	
Q1P105	0501-000616	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1W,TO-92L	
Q1P106	0501-000616	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1W,TO-92L	
Q1P107	0501-000616	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1W,TO-92L	
Q1P108	0504-000142	TR-DIGITAL;KSR2001,PNP,300MW,4.7K/4.7K,T	
Q1P109	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
Q1P110	0501-000616	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1W,TO-92L	
Q1P111	0501-000616	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1W,TO-92L	
R1P101	2001-000855	R-CARBON;560OHM,5%,1/4W,AA,TP,2.4X6.4MM	
R1P103	2001-000362	R-CARBON;150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1P104	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R1P105	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1P109	2001-000362	R-CARBON;150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1P110	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R1P111	2001-000062	R-CARBON;470OHM,5%,1/4W,AA,TP,2.4X6.4MM	
R1P112	2001-000302	R-CARBON;10OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1P120	2001-000855	R-CARBON;560OHM,5%,1/4W,AA,TP,2.4X6.4MM	
VA01	1405-001026	VARISTOR;470V,600A,9x7mm,TP	
ZD1P02	0403-001211	DIODE-ZENER;MTZJ12B,11.44-12.03V,500MW,D	
ZD1P03	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	

Loc.No	Part No	Description ; Specification	Remark
ZD1P04	0403-000717	DIODE-ZENER;MTZJ5.1B,5.1V,4.94-5.2V,500m	
ZD1P05	0403-001211	DIODE-ZENER;MTZJ12B,11.44-12.03V,500MW,D	
ZD1P06	0403-000717	DIODE-ZENER;MTZJ5.1B,5.1V,4.94-5.2V,500m	
ZD1P1A	0403-001211	DIODE-ZENER;MTZJ12B,11.44-12.03V,500MW,D	
SYSTEM CONTROL/SERVO PARTS			
C601	2203-000609	C-CERAMIC,CHIP;22nF,10%,50V,X7R,TP,2012	
C601A	2203-000634	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,201	
C601B	2203-000634	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,201	
C602	2401-002095	C-AL;47uF,20%,25V,GP,TP,6.3x5,5	
C602A	2203-000634	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,201	
C602B	2203-000634	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,201	
C603	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C604	2203-000609	C-CERAMIC,CHIP;22nF,10%,50V,X7R,TP,2012	
C605	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
C606	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
C607	2401-000118	C-AL;1000uF,20%,10V,GP,TP,10x12.5,5	
C608	2401-002259	C-AL;0.1F,+80-20%,5.5V,-,TP,12.5x11	BACK-UP(1HOUR) Option
C610	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
C618	2401-000360	C-AL;100uF,20%,50V,GP,TP,8x11.5,5	
C619	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
C623	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
C624	2203-000634	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,201	BACK-UP(1HOUR) Option
C625	2203-000634	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,201	BACK-UP(1HOUR) Option
C626	2203-000634	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,201	
C627	2203-000634	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,201	
C632	2203-000802	C-CERAMIC,CHIP;33nF,10%,50V,X7R,TP,2012	
C633	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
C634	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
C635	2202-000183	C-CERAMIC,MLC-AXIAL;2.2NF,20%,16V,Y5R,TP	
C636	2202-000183	C-CERAMIC,MLC-AXIAL;2.2NF,20%,16V,Y5R,TP	
C637	2203-000938	C-CERAMIC,CHIP;0.47nF,5%,50V,NP0,TP,2012	
C638	2401-002196	C-AL;4.7UF,20,25V,GP,TP,4X5,5MM,-	
C639	2203-000239	C-CERAMIC,CHIP;0.1nF,5%,50V,NP0,TP,2012	
C640	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
C641	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
C642	2401-001507	C-AL;47uF,20%,16V,GP,TP,6.3x5,5	
C645	2203-000361	C-CERAMIC,CHIP;0.15nF,5%,50V,NP0,TP,2012	
C646	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C659	2203-001137	C-CERAMIC,CHIP;68nF,+80-20%,50V,Y5V,TP,2	
C661	2203-000989	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012	
C688	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C691	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
C695	2203-000361	C-CERAMIC,CHIP;0.15nF,5%,50V,NP0,TP,2012	
C696	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
CN603	3710-001146	CONNECTOR-SOCKET;20P,1R,1.5mm,ANGLE,SN	
CN604	3711-004833	CONNECTOR-HEADER;BOX,12P,2R,2MM,STRAIGHT	
D603	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
D620	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
D688	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
D692	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
IC601	AC09-00030A	IC MICOM;UPD790006GF-3BA,100PIN,QFP,-,1	
IC604	AC14-12006C	IC;KA7533,DIP,-	
IC605	1103-001148	IC-EEPROM;24C021,2KBIT,DIP,8P,300MIL,10M	
IC608	1203-000515	IC-VOL. DETECTOR;7042,TO-92,3P,177MIL,PL	BACK-UP(1HOUR) Option
L603	2701-000002	INDUCTOR-AXIAL;100uH,10%,4.2x9.8mm	
L605	2701-000002	INDUCTOR-AXIAL;100uH,10%,4.2x9.8mm	
LD601	0601-000517	LED-IR;RECTANGULA,4x6.0mm,75mW,6V,950	
PT601	0604-001206	PHOTO-INTERRUPTER;TR,-,150mW,CY5894102,B	
PT602	0604-001206	PHOTO-INTERRUPTER;TR,-,150mW,CY5894102,B	
Q601	0504-000119	TR-DIGITAL;KSR1004,NPN,300MW,47K/47K,TO-	
Q602	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
R608	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012	
R609	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R610	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R612	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	

Loc.No	Part No	Description ; Specification	Remark
R613	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	BACK-UP(1HOUR) Option
R614	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R615	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R617	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012	
R630	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R631	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
R640	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R641	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R642	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R644	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R647	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R651	2001-000010	R-CARBON;68KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R652	2001-000568	R-CARBON;27OHM,5%,1/8W,AA,TP,1.8X3.2MM	BACK-UP(1HOUR) Option
R657	2007-001124	R-CHIP;68KOHM,1%,1/10W,DA,TP,2012	BACK-UP(1HOUR) Option
R660	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
R661	2007-000774	R-CHIP;33KOHM,5%,1/10W,DA,TP,2012	
R666	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
R667	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
R668	2007-000931	R-CHIP;470OHM,5%,1/10W,DA,TP,2012	
R669	2007-000931	R-CHIP;470OHM,5%,1/10W,DA,TP,2012	
R670	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
R671	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
R672	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
R673	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R674	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R675	2001-000032	R-CARBON;180OHM,5%,1/4W,AA,TP,2.4X6.4MM	
R676	2007-000738	R-CHIP;30KOHM,5%,1/10W,DA,TP,2012	
R677	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R678	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
R679	2007-000572	R-CHIP;220OHM,5%,1/10W,DA,TP,2012	
R682	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
R685	2007-000981	R-CHIP;5.6KOHM,5%,1/10W,DA,TP,2012	
R688	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R691	2007-000572	R-CHIP;220OHM,5%,1/10W,DA,TP,2012	
R693	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R694	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
R698	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
S601	0603-001011	PHOTO TR;NPN,35V,6V,50mA,75mW,BK	
S602	0603-001011	PHOTO TR;NPN,35V,6V,50mA,75mW,BK	
SW601	AC34-20100A	SWITCH-MODE;-,-,X-9,-	
SW602	AC34-20100B	SWITCH-REC;-,-,X-9,-	
W666	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
W676	2701-000238	INDUCTOR-AXIAL;1.8uH,10%,2.5x3.4mm	
XT601	2801-003318	CRYSTAL-UNIT;32.768KHz,20ppm,28-AAP,12.5	BACK-UP(1HOUR) Option
XT602	2801-003139	CRYSTAL-UNIT;8MHz,50ppm,28-AAA,22pF,80oh	
A/V PARTS			
C315	2203-000989	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012	
C317	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C318	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C319	2203-000844	C-CERAMIC,CHIP;39nF,10%,50V,X7R,TP,2012,	
C320	2203-000989	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012	
C321	2203-000609	C-CERAMIC,CHIP;22nF,10%,50V,X7R,TP,2012	
C322	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C324	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
C325	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C326	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C327	2203-001214	C-CERAMIC,CHIP;8.2nF,10%,50V,X7R,TP,2012	
C328	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
C329	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
C330	2203-000989	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012	
C331	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	Not used Australia Model
C332	2202-002055	C-CERAMIC,MLC-AXIAL;47nF,+80-20%,50V,Y5V	
C333	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C335	2203-000925	C-CERAMIC,CHIP;470NF,+80-20%,50V,Y5V,TP,	
C336	2203-000989	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012	

Loc.No	Part No	Description ; Specification	Remark
C337	2203-000925	C-CERAMIC,CHIP;470NF,+80-20%,50V,Y5V,TP,	
C338	2203-000609	C-CERAMIC,CHIP;22nF,10%,50V,X7R,TP,2012	
C339	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C340	2401-001226	C-AL;4.7uF,20%,16V,BP,TP,4x7,5mm	
C341	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C342	2202-000797	C-CERAMIC,MLC-AXIAL;10NF,30%,16V,Y5S,TP,	
C343	2203-000476	C-CERAMIC,CHIP;1000nF,+80-20%,16V,Y5V,TP	
C344	2203-000321	C-CERAMIC,CHIP;0.12nF,5%,50V,SL,TP,2012	
C345	2203-000595	C-CERAMIC,CHIP;0.22nF,5%,50V,NP0,TP,2012	
C347	2203-000476	C-CERAMIC,CHIP;1000nF,+80-20%,16V,Y5V,TP	
C348	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
C349	2203-000476	C-CERAMIC,CHIP;1000nF,+80-20%,16V,Y5V,TP	
C350	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
C351	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C352	2401-001915	C-AL;1uF,20%,50V,GP,TP,3x5,5	
C353	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C354	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C355	2202-000644	C-CERAMIC,MLC-AXIAL;33nF,10%,50V,X7R,TP,	
C372	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
C380	2203-000609	C-CERAMIC,CHIP;22nF,10%,50V,X7R,TP,2012	
C384	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C385	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
C393	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
C395	2202-000797	C-CERAMIC,MLC-AXIAL;10NF,30%,16V,Y5S,TP,	
C396	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
C397A	2203-000661	C-CERAMIC,CHIP;0.27nF,5%,50V,NP0,TP,2012	
C398	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
C3A01	2401-003122	C-AL;4.7uF,20%,50V,LL,TP,4X7,1.5	
C3A02	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	
C3A08	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
C3A09	2203-001105	C-CERAMIC,CHIP;6.8nF,10%,50V,X7R,TP,2012	
C3A10	2203-001214	C-CERAMIC,CHIP;8.2nF,10%,50V,X7R,TP,2012	
C3A11	2301-000176	C-FILM,PEF;18nF,5%,100V,TP,10X9X4.3X5,5m	
C3A12	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C3A14	2203-000938	C-CERAMIC,CHIP;0.47nF,5%,50V,NP0,TP,2012	
C3A15	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
C3A16	2401-003122	C-AL;4.7uF,20%,50V,LL,TP,4X7,1.5	
C3A17	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C3A18	2203-001128	C-CERAMIC,CHIP;0.68nF,10%,50V,X7R,TP,201	
C3A21	2203-000170	C-CERAMIC,CHIP;1.8nF,10%,50V,X7R,TP,2012	
C3A23	2401-002069	C-AL;33uF,20%,16V,GP,TP,6.3x5,5	
C3A24	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C3A29	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
C3A30	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C3A40	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C3A41	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C3A51	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	MONO Models Only
C3A52	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	MONO Models Only
C3A54	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	MONO Models Only
C3D01	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5	A.DUB OPTION
C3D02	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	A.DUB OPTION
C3D03	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	A.DUB OPTION
C3D04	2203-000361	C-CERAMIC,CHIP;0.15nF,5%,50V,NP0,TP,2012	A.DUB OPTION
C3Q1	2202-000797	C-CERAMIC,MLC-AXIAL;10NF,30%,16V,Y5S,TP,	
C3Q2	2203-000818	C-CERAMIC,CHIP;0.033nF,5%,50V,NP0,TP,201	
C3Q3	2203-001088	C-CERAMIC,CHIP;0.005nF,0.25pF,50V,NP0,TP	
C3Q4	2202-000797	C-CERAMIC,MLC-AXIAL;10NF,30%,16V,Y5S,TP,	
CN301	3708-000391	CONNECTOR-FPC/FFC/PIC;10P,1.25mm,STRAIGH	HI-FI Models
	3708-000394	CONNECTOR-FPC/FFC/PIC;6P,1.25mm,STRAIGHT	MONO Models
CN3A01	3708-001165	CONNECTOR-FPC/FFC/PIC;6P,1.25mm,STRAIGHT	
CN3A02	3710-001648	CONNECTOR-SOCKET;2P,1R,2.5mm,STRAIGHT,SN	
D301	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
D302	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
FL3A01	2702-000166	INDUCTOR-RADIAL;47uH,5%,6x6.4mm	
FL3D01	2702-000166	INDUCTOR-RADIAL;47uH,5%,6x6.4mm	A.DUB OPTION
IC301	1204-001923	IC-VIDEO PROCESS;LA71730M,QFP,100P-,PLA	

Loc.No	Part No	Description ; Specification	Remark
IC302	1204-001748	IC-SELECTOR;MM1503XN,SOP,6P,63MIL,PLASTI	MONO Models Only
L302	2702-000106	INDUCTOR-RADIAL;100uH,10%,6.2x7.4mm	
L304	3301-000297	CORE-FERRITE BEAD;AA,3.6x1.2x5.7mm,1400,	
L370	2702-000106	INDUCTOR-RADIAL;100uH,10%,6.2x7.4mm	
L3A01	2702-000120	INDUCTOR-RADIAL;15mH,5%,6.2x7.4mm	
L3A02	2702-000106	INDUCTOR-RADIAL;100uH,10%,6.2x7.4mm	
L3A03	2701-000002	INDUCTOR-AXIAL;100uH,10%,4.2x9.8mm	
L3A50	2702-000119	INDUCTOR-RADIAL;150uH,5%,6x6.4mm	A.DUB OPTION
L3D01	2701-000002	INDUCTOR-AXIAL;100uH,10%,4.2x9.8mm	A.DUB OPTION
L3Q1	2701-000206	INDUCTOR-AXIAL;56uH,5%,2.4x3.4mm	
L3Q2	2701-000131	INDUCTOR-AXIAL;15uH,5%,2.5x3.4mm	
Q350	0501-000303	TR-SMALL SIGNAL;KSA733,PNP,250mW,TO-92,T	
Q3A01	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
Q3A02	0501-000303	TR-SMALL SIGNAL;KSA733,PNP,250mW,TO-92,T	
Q3A03	0501-000442	TR-SMALL SIGNAL;KTC3203-Y,NPN,400mW,T0-9	
Q3A04	0501-000442	TR-SMALL SIGNAL;KTC3203-Y,NPN,400mW,T0-9	
Q3A05	0501-000442	TR-SMALL SIGNAL;KTC3203-Y,NPN,400mW,T0-9	
Q3A06	0501-000303	TR-SMALL SIGNAL;KSA733,PNP,250mW,TO-92,T	
Q3D01	0501-000442	TR-SMALL SIGNAL;KTC3203-Y,NPN,400mW,T0-9	A.DUB OPTION
Q3D02	0501-000303	TR-SMALL SIGNAL;KSA733,PNP,250mW,TO-92,T	A.DUB OPTION
Q3D07	0504-000119	TR-DIGITAL;KSR1004,NPN,300MW,47K/47K,TO-	A.DUB OPTION
Q3Q1	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
Q3Q2	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
Q3Q3	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
Q3Q4	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
Q3Q5	0504-000142	TR-DIGITAL;KSR2001,PNP,300MW,4.7K/4.7K,T	
Q3Q6	0504-000119	TR-DIGITAL;KSR1004,NPN,300MW,47K/47K,TO-	
Q3Q7	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
R315	2007-000221	R-CHIP;1.2KOHM,5%,1/10W,DA,TP,2012	
R316	2007-001177	R-CHIP;8.2KOHM,5%,1/10W,DA,TP,2012	
R320	2001-000411	R-CARBON;18KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R321	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R322	2001-000411	R-CARBON;18KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R323	2007-000710	R-CHIP;3.9KOHM,5%,1/10W,DA,TP,2012	
R325	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R326	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R327	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
R328	2007-000221	R-CHIP;1.2KOHM,5%,1/10W,DA,TP,2012	
R329	2007-000518	R-CHIP;2.7KOHM,5%,1/10W,DA,TP,2012	
R330	2007-001071	R-CHIP;6.8KOHM,5%,1/10W,DA,TP,2012	
R331	2007-000267	R-CHIP;1.8KOHM,5%,1/10W,DA,TP,2012	
R333	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012	
R334	2007-000241	R-CHIP;1.5KOHM,5%,1/10W,DA,TP,2012	HI-FI Models
R334	2007-000221	R-CHIP;1.2KOHM,5%,1/10W,DA,TP,2012	MONO Models
R335	2007-000290	R-CHIP;100OHM,5%,1/10W,DA,TP,2012	
R370	2007-000030	R-CHIP;560OHM,5%,1/10W,DA,TP,2012	
R372	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
R373	2007-000546	R-CHIP;20KOHM,5%,1/10W,DA,TP,2012	
R374	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R380	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
R3A01	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R3A04	2007-000221	R-CHIP;1.2KOHM,5%,1/10W,DA,TP,2012	
R3A05	2007-000615	R-CHIP;24KOHM,5%,1/10W,DA,TP,2012	
R3A06	2007-000449	R-CHIP;180OHM,5%,1/10W,DA,TP,2012	
R3A07	2007-000757	R-CHIP;330KOHM,5%,1/10W,DA,TP,2012	
R3A08	2001-000331	R-CARBON;12KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R3A11	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
R3A12	2007-000290	R-CHIP;100OHM,5%,1/10W,DA,TP,2012	
R3A13	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	DVD-V85K Only
	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	Other Models
R3A14	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R3A16	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
R3A17	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
R3A18	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
R3A23	2001-000331	R-CARBON;12KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R3A24	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	

Loc.No	Part No	Description ; Specification	Remark
R3A25	2007-000221	R-CHIP;1.2KOHM,5%,1/10W,DA,TP,2012	
R3A26	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R3A28	2001-000258	R-CARBON;1.8KOHM,5%,1/8W,AA,TP,1.8X3.2M	HI-FI Models
	2001-000812	R-CARBON;5.6KOHM,5%,1/8W,AA,TP,1.8X3.2M	MONO Models
R3A32	2001-000766	R-CARBON;43KOHM,5%,1/8W,AA,TP,1.8X3.2MM	MONO Models Only
R3A50	2007-000964	R-CHIP;5.1KOHM,5%,1/10W,DA,TP,2012	
R3A51	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
R3A52	2001-000613	R-CARBON;3.9KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R3A60	2007-000703	R-CHIP;3.6KOHM,5%,1/10W,DA,TP,2012	
R3D01	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	A.DUB OPTION
R3D02	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	A.DUB OPTION
R3D03	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	A.DUB OPTION
R3D04	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	A.DUB OPTION
R3Q1	2007-000221	R-CHIP;1.2KOHM,5%,1/10W,DA,TP,2012	
R3Q12	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R3Q2	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
R3Q3	2007-000766	R-CHIP;330OHM,5%,1/10W,DA,TP,2012	
R3Q4	2007-001055	R-CHIP;6.2KOHM,5%,1/10W,DA,TP,2012	
R3Q5	2007-000766	R-CHIP;330OHM,5%,1/10W,DA,TP,2012	
R3Q6	2007-000258	R-CHIP;1.6KOHM,5%,1/10W,DA,TP,2012	
R3Q7	2007-000844	R-CHIP;3KOHM,5%,1/10W,DA,TP,2012	
R3Q8	2007-000766	R-CHIP;330OHM,5%,1/10W,DA,TP,2012	
R3Q9	2007-001155	R-CHIP;750OHM,5%,1/10W,DA,TP,2012	
XT301	2801-001397	CRYSTAL-UNIT;4.433619MHz,20ppm,28-AAA,S,	
XT302	2801-003399	CRYSTAL-UNIT;3.579545MHz,15ppm,28-AAA,S,	
TM-BLOCK(DVD-V85K/V72K Only)			
C401	2401-001479	C-AL;470uF,20%,10V,GP,TP,-,-	
C401A	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C402	2202-000807	C-CERAMIC,MLC-AXIAL;22nF,+80-20%,25V,Y5V	
C403	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C404	2401-001085	C-AL;330nF,20%,50V,GP,-,5x9,2mm	
C405	2401-003046	C-AL;47uF,20%,50V,WT,TP,6.3x11,2.5	
C406	2202-000797	C-CERAMIC,MLC-AXIAL;10NF,30%,16V,Y5S,TP,	
C407	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C408	2202-000797	C-CERAMIC,MLC-AXIAL;10NF,30%,16V,Y5S,TP,	
C410	2202-000797	C-CERAMIC,MLC-AXIAL;10NF,30%,16V,Y5S,TP,	
D401	2701-000002	INDUCTOR-AXIAL;100uH,10%,4.2x9.8mm	
L402	2701-000002	INDUCTOR-AXIAL;100uH,10%,4.2x9.8mm	
R401	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R401A	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R402	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R402A	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R403	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R404	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R406	2001-000837	R-CARBON;51KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R408	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
TM401	AC40-00014A	TM BLOCK;TCMK0601PD13A,G/I/K(MONO,HIFI)	
W414	2701-000002	INDUCTOR-AXIAL;100uH,10%,4.2x9.8mm	
W442	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
W443	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
W444	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
ZD401	0403-000390	DIODE-ZENER;UZP33B,33V,31.4-34.6V,1W,DO-	
HI-FI/MTS PARTS(HI-FI Models Only)			
C501	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C502	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
C503	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	
C504	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C505	2401-001250	C-AL;4.7uF,20%,35V,GP,TP,4x5,5	
C506	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
C507	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	
C508	2203-000891	C-CERAMIC,CHIP;4.7nF,10%,50V,X7R,TP,2012	
C510	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C511	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
C513	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	

Loc.No	Part No	Description ; Specification	Remark
C517	2203-000891	C-CERAMIC,CHIP;4.7nF,10%,50V,X7R,TP,2012	
C518	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	
C519	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
C520	2401-001250	C-AL;4.7uF,20%,35V,GP,TP,4x5,5	
C521	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C522	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
C523	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
C524	2401-001250	C-AL;4.7uF,20%,35V,GP,TP,4x5,5	
C525	2401-001250	C-AL;4.7uF,20%,35V,GP,TP,4x5,5	
C526	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
C527	2202-000797	C-CERAMIC,MLC-AXIAL;10NF,30%,16V,Y5S,TP,	
C529	2401-001250	C-AL;4.7uF,20%,35V,GP,TP,4x5,5	
C530	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
C535	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
C536	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
C537	2401-000665	C-AL;2.2uF,20%,50V,GP,TP,3.5x5,5	
C538	2401-000665	C-AL;2.2uF,20%,50V,GP,TP,3.5x5,5	
C541	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C542	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
D501	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
IC501	1204-001920	IC-AUDIO PROCESSOR;LA72646M,QFP,80P,14X1	
R501	2007-000003	R-CHIP;43KOHM,5%,1/10W,DA,TP,2012	
R502	2007-001055	R-CHIP;6.2KOHM,5%,1/10W,DA,TP,2012	
R503	2007-000931	R-CHIP;470OHM,5%,1/10W,DA,TP,2012	
R505	2007-000003	R-CHIP;43KOHM,5%,1/10W,DA,TP,2012	
R506	2007-001055	R-CHIP;6.2KOHM,5%,1/10W,DA,TP,2012	
R509	2007-001071	R-CHIP;6.8KOHM,5%,1/10W,DA,TP,2012	
R510	2007-000003	R-CHIP;43KOHM,5%,1/10W,DA,TP,2012	
R511	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
R512	2007-000774	R-CHIP;33KOHM,5%,1/10W,DA,TP,2012	
R514	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
R516	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
R517	2007-001071	R-CHIP;6.8KOHM,5%,1/10W,DA,TP,2012	
R518	2001-000766	R-CARBON;43KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R521	2007-001071	R-CHIP;6.8KOHM,5%,1/10W,DA,TP,2012	
R522	2007-001071	R-CHIP;6.8KOHM,5%,1/10W,DA,TP,2012	
R533	2007-000003	R-CHIP;43KOHM,5%,1/10W,DA,TP,2012	
R540	2001-000766	R-CARBON;43KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R545	2001-000006	R-CARBON;2.4KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R546	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
R547	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
R550	2001-000766	R-CARBON;43KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R551	2007-000546	R-CHIP;20KOHM,5%,1/10W,DA,TP,2012	
R552	2007-000003	R-CHIP;43KOHM,5%,1/10W,DA,TP,2012	
R553	2007-000546	R-CHIP;20KOHM,5%,1/10W,DA,TP,2012	
R570	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
R571	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012	
W586	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
A2/NICAM PARTS(DVD-V85K/V72K Only)			
C4N01	2202-000848	C-CERAMIC,MLC-AXIAL;1.5nF,30%,50V,Y5S,TP	
C4N02	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C4N03	2202-000806	C-CERAMIC,MLC-AXIAL;220pF,10%,50V,Y5P,TP	
C4N04	2401-000665	C-AL;2.2uF,20%,50V,GP,TP,3.5x5,5	
C4N05	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
C4N06	2202-000797	C-CERAMIC,MLC-AXIAL;10NF,30%,16V,Y5S,TP,	
C4N07	2202-000263	C-CERAMIC,MLC-AXIAL;470pF,10%,50V,Y5P,TP	
C4N08	2202-000848	C-CERAMIC,MLC-AXIAL;1.5nF,30%,50V,Y5S,TP	
C4N09	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C4N10	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C4N11	2401-001020	C-AL;3.3UF,20%,50V,GP,TP,4X7,5	
C4N12	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C4N13	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C4N14	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C4N15	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C4N16	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	

Loc.No	Part No	Description ; Specification	Remark
C4N17	2202-000263	C-CERAMIC,MLC-AXIAL;470pF,10%,50V,Y5P,TP	
C4N18	2202-000263	C-CERAMIC,MLC-AXIAL;470pF,10%,50V,Y5P,TP	
C4N19	2202-000279	C-CERAMIC,MLC-AXIAL;47pF,5%,50V,SL,TP,3.	
C4N21	2201-002069	C-CERAMIC,DISC;1.5pF,0.25pF,50V,NP0,TP,4	
C4N22	2201-002069	C-CERAMIC,DISC;1.5pF,0.25pF,50V,NP0,TP,4	
C4N23	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C4N24	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C4N25	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C4N30	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
D4N01	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
D4N02	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
IC4N01	1204-001765	IC-AUDIO PROCESSOR;MSP3417D(PQFP),PQFP,4	
L4N01	2702-000160	INDUCTOR-RADIAL;4.7uH,10%,6x6.4mm	
L4N02	2702-000106	INDUCTOR-RADIAL;100uH,10%,6.2x7.4mm	
L4N03	2702-000160	INDUCTOR-RADIAL;4.7uH,10%,6x6.4mm	
L4N04	3301-000297	CORE-FERRITE BEAD;AA,3.6x1.2x5.7mm,1400,	
R4N01	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R4N02	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R4N03	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R4N04	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R4N05	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R4N06	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
XT4N01	2801-004096	CRYSTAL-UNIT;18.432MHZ,20PPM,28-AAA,16PF	
OSD/VPS/PDC PARTS			
C6P01	2202-000797	C-CERAMIC,MLC-AXIAL;10NF,30%,16V,Y5S,TP,	
C6P01A	2401-001479	C-AL;470uF,20%,10V,GP,TP,-,-	
C6P02	2202-000145	C-CERAMIC,MLC-AXIAL;.12NF,10%,50V,Y5P,TP	
C6P04	2203-000683	C-CERAMIC,CHIP;0.027nF,5%,50V,NP0,TP,201	
C6P05	2203-000683	C-CERAMIC,CHIP;0.027nF,5%,50V,NP0,TP,201	
C6P08	2202-000286	C-CERAMIC,MLC-AXIAL;56pF,5%,50V,SL,TP,1.	
C6P10	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C6P11	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C6P12	2401-001479	C-AL;470uF,20%,10V,GP,TP,-,-	
C6P13	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
C6P15	2203-001137	C-CERAMIC,CHIP;68nF,+80-20%,50V,Y5V,TP,2	
D6P01	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
IC6P01	1204-001998	IC-OSD PROCESSOR;LC74759JM-9843,MFP,24P,	DVD-V85K/V72K/V52 Only
	1204-001796	IC-OSD PROCESSOR;LC74759JM-9820,MFP,24P,	Other Models
L6P03	2702-000142	INDUCTOR-RADIAL;22uH,5%,6x6.4mm	
L6P05	2701-000165	INDUCTOR-AXIAL;27uH,5%,2.4x3.4mm	
Q6P01	0501-000303	TR-SMALL SIGNAL;KSA733,PNP,250mW,TO-92,T	
Q6P02	0501-000303	TR-SMALL SIGNAL;KSA733,PNP,250mW,TO-92,T	
Q6P04	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
R6P05	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R6P07	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R6P08	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R6P09	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R6P10	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R6P12	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
R6P13	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
R6P14	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2M	
KARAOKE PARTS(Not used DVD-V52)			
CK01	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
CK01A	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
CK02	2203-001193	C-CERAMIC,CHIP;0.075nF,5%,50V,NP0,TP,201	
CK04	2203-000476	C-CERAMIC,CHIP;1000nF,+80-20%,16V,Y5V,TP	
CK06	2203-001193	C-CERAMIC,CHIP;0.075nF,5%,50V,NP0,TP,201	
CK07	2203-000476	C-CERAMIC,CHIP;1000nF,+80-20%,16V,Y5V,TP	
CK21	2203-000192	C-CERAMIC,CHIP;100nF,+80-20%,50V,Y5V,TP,	
CK22	2401-001915	C-AL;1uF,20%,50V,GP,TP,3x5,5	
CK23	2203-000239	C-CERAMIC,CHIP;0.1nF,5%,50V,NP0,TP,2012	
CK25	2401-001775	C-AL;470nF,20%,50V,GP,TP,4x7,5	
CK26	2401-001915	C-AL;1uF,20%,50V,GP,TP,3x5,5	
CK27	2202-000173	C-CERAMIC,MLC-AXIAL;1nF,10%,50V,Y5P,TP,1	

Loc.No	Part No	Description ; Specification	Remark
CK28	2203-001592	C-CERAMIC,CHIP;1nF,5%,50V,X7R,TP,2012	
CK29	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
CK31	2203-000192	C-CERAMIC,CHIP;100nF,+80-20%,50V,Y5V,TP,	
CK33	2203-000634	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,201	
CK34	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
CK35	2203-000634	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,201	
CK42	2401-001915	C-AL;1uF,20%,50V,GP,TP,3x5,5	
CK43	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	
CK44	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
CK45	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
CK46	2203-000839	C-CERAMIC,CHIP;0.39nF,5%,50V,NP0,TP,2012	
CK47	2203-000716	C-CERAMIC,CHIP;3.3nF,10%,50V,X7R,TP,2012	
CK48	2401-000665	C-AL;2.2uF,20%,50V,GP,TP,3.5x5,5	
CK49	2203-000192	C-CERAMIC,CHIP;100nF,+80-20%,50V,Y5V,TP,	
CK50	2203-000891	C-CERAMIC,CHIP;4.7nF,10%,50V,X7R,TP,2012	
CK51	2203-000891	C-CERAMIC,CHIP;4.7nF,10%,50V,X7R,TP,2012	
CK52	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
CK53	2203-000323	C-CERAMIC,CHIP;12nF,10%,50V,X7R,TP,2012,	
CK54	2203-000891	C-CERAMIC,CHIP;4.7nF,10%,50V,X7R,TP,2012	
CK55	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
CK56	2203-000192	C-CERAMIC,CHIP;100nF,+80-20%,50V,Y5V,TP,	
CK57	2401-001507	C-AL;47uF,20%,16V,GP,TP,6.3x5,5	
CK58	2203-000476	C-CERAMIC,CHIP;1000nF,+80-20%,16V,Y5V,TP	
CK61	2203-001724	C-CERAMIC,CHIP;4700NF,+80-20%,16V,Y5V,TP	
CK62	2203-001724	C-CERAMIC,CHIP;4700NF,+80-20%,16V,Y5V,TP	
CK63	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
CK64	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
CK65	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
CK66	2203-001592	C-CERAMIC,CHIP;1nF,5%,50V,X7R,TP,2012	
CK67	2203-000192	C-CERAMIC,CHIP;100nF,+80-20%,50V,Y5V,TP,	
CK68	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
CK69	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
CK70	2203-000595	C-CERAMIC,CHIP;0.22nF,5%,50V,NP0,TP,2012	
CK71	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
CK90	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
CK91	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
CK92	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
ICK1	1201-000163	IC-OP AMP;4560,SOP,8P,173MIL,DUAL,100V/m	
ICK2	1201-000163	IC-OP AMP;4560,SOP,8P,173MIL,DUAL,100V/m	
ICK3	1201-000163	IC-OP AMP;4560,SOP,8P,173MIL,DUAL,100V/m	
ICK4	1204-001730	IC-ECHO;M65855P,DIP,16P,300MIL,PLASTIC	
ICK5	AC14-12007G	IC-LINEAR;KA22134,DIP,AMP,STICK	
QK1	0501-000442	TR-SMALL SIGNAL;KTC3203-Y,NPN,400mW,T0-9	
QK2	0501-000442	TR-SMALL SIGNAL;KTC3203-Y,NPN,400mW,T0-9	
RK02	2007-000653	R-CHIP;27KOHM,5%,1/10W,DA,TP,2012	
RK03	2007-000653	R-CHIP;27KOHM,5%,1/10W,DA,TP,2012	
RK04	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
RK05	2007-000572	R-CHIP;220OHM,5%,1/10W,DA,TP,2012	
RK07	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
RK08	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
RK09	2007-000653	R-CHIP;27KOHM,5%,1/10W,DA,TP,2012	
RK10	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
RK12	2007-000653	R-CHIP;27KOHM,5%,1/10W,DA,TP,2012	
RK13	2007-000572	R-CHIP;220OHM,5%,1/10W,DA,TP,2012	
RK21	2007-000409	R-CHIP;15KOHM,5%,1/10W,DA,TP,2012	
RK22	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
RK23	2007-000409	R-CHIP;15KOHM,5%,1/10W,DA,TP,2012	
RK25	2001-000508	R-CARBON;220KOHM,5%,1/8W,AA,TP,1.8X3.2M	
RK26	2007-001124	R-CHIP;68KOHM,1%,1/10W,DA,TP,2012	
RK27	2001-000362	R-CARBON;150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
RK28	2007-000409	R-CHIP;15KOHM,5%,1/10W,DA,TP,2012	
RK31	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M	
RK32	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
RK34	2001-000411	R-CARBON;18KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
RK41	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
RK43	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	

Loc.No	Part No	Description ; Specification	Remark
RK44	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
RK45	2007-000409	R-CHIP;15KOHM,5%,1/10W,DA,TP,2012	
RK46	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
RK47	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
RK48	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2M	
RK49	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
RK50	2007-000774	R-CHIP;33KOHM,5%,1/10W,DA,TP,2012	
RK51	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
RK52	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
RK53	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
RK54	2007-001177	R-CHIP;8.2KOHM,5%,1/10W,DA,TP,2012	
RK55	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
RK56	2001-000319	R-CARBON;120KOHM,5%,1/8W,AA,TP,1.8X3.2M	
RK61	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
RK62	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
RK65	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
RK66	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
RK67	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
RK68	2007-000409	R-CHIP;15KOHM,5%,1/10W,DA,TP,2012	
RK69	2007-000290	R-CHIP;100OHM,5%,1/10W,DA,TP,2012	
RK70	2007-000774	R-CHIP;33KOHM,5%,1/10W,DA,TP,2012	
RK71	2007-000738	R-CHIP;30KOHM,5%,1/10W,DA,TP,2012	
RK72	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
RK73	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
RK74	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
RK75	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
RK77	2007-000653	R-CHIP;27KOHM,5%,1/10W,DA,TP,2012	
INPUT-OUTPUT PARTS			
C818	2203-000784	C-CERAMIC,CHIP;0.33nF,5%,50V,NP0,TP,2012	
C819	2203-000784	C-CERAMIC,CHIP;0.33nF,5%,50V,NP0,TP,2012	
C820	2203-000784	C-CERAMIC,CHIP;0.33nF,5%,50V,NP0,TP,2012	
C821	2203-000784	C-CERAMIC,CHIP;0.33nF,5%,50V,NP0,TP,2012	
C822	2203-000239	C-CERAMIC,CHIP;0.1nF,5%,50V,NP0,TP,2012	
C833	2203-000239	C-CERAMIC,CHIP;0.1nF,5%,50V,NP0,TP,2012	
C835	2401-001479	C-AL;470uF,20%,10V,GP,TP,-,-	
C836	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
C853	2203-000891	C-CERAMIC,CHIP;4.7nF,10%,50V,X7R,TP,2012	
C854	2203-000891	C-CERAMIC,CHIP;4.7nF,10%,50V,X7R,TP,2012	
JC803	3722-001577	JACK-PIN;6P,3.5mm,NI,BLK,-	HI-FI Models
	3722-001575	JACK-PIN;4P/6P,3.5mm,NI,BLK,-	MONO Models
L803	2701-000181	INDUCTOR-AXIAL;33uH,5%,2.4x3.4mm	
L804	2701-000181	INDUCTOR-AXIAL;33uH,5%,2.4x3.4mm	
L809	2701-000181	INDUCTOR-AXIAL;33uH,5%,2.4x3.4mm	
L810	2701-000181	INDUCTOR-AXIAL;33uH,5%,2.4x3.4mm	
Q811	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
R805	2007-000642	R-CHIP;270OHM,5%,1/10W,DA,TP,2012	
R806	2007-000642	R-CHIP;270OHM,5%,1/10W,DA,TP,2012	
R812	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R815	2007-000642	R-CHIP;270OHM,5%,1/10W,DA,TP,2012	
R816	2007-000642	R-CHIP;270OHM,5%,1/10W,DA,TP,2012	
R843	2007-000030	R-CHIP;560OHM,5%,1/10W,DA,TP,2012	
R844	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
W710	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
W716	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
W717	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
W718	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
W722	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	

Loc.No	Part No	Description ; Specification	Remark
602	**-**	**ASSY PCB-MAIN(DVD);**	
AC14	2203-001607	C-CERAMIC,CHIP;0.22nF,5%,50V,NP0,TP,1608	
AC15	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
AC16	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
AC17	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
AC18	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
AC19	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
AC20	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
AC21	2203-000315	C-CERAMIC,CHIP;0.12nF,5%,50V,NP0,TP,1608	
AC22	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
AC23	2203-000125	C-CERAMIC,CHIP;1.2nF,10%,50V,X7R,TP,1608	
AC24	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
AC25	2203-000315	C-CERAMIC,CHIP;0.12nF,5%,50V,NP0,TP,1608	
AC26	2203-000125	C-CERAMIC,CHIP;1.2nF,10%,50V,X7R,TP,1608	
AC27	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
AC9	2203-001607	C-CERAMIC,CHIP;0.22nF,5%,50V,NP0,TP,1608	
AD1	0407-000114	DIODE-ARRAY;DAN202K,80V,100mA,CA2-3,SOT-	
AD2	0407-000114	DIODE-ARRAY;DAN202K,80V,100mA,CA2-3,SOT-	
AD3	0407-000114	DIODE-ARRAY;DAN202K,80V,100mA,CA2-3,SOT-	
AD4	0401-000008	DIODE-SWITCHING;DAN217,80V,100mA,SOT-23,	
AD5	0407-000114	DIODE-ARRAY;DAN202K,80V,100mA,CA2-3,SOT-	
AD6	0407-000116	DIODE-ARRAY;DAP202K,80V,100mA,CK2-3,SOT-	
AE10	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
AE11	2401-000913	C-AL;22uF,20%,16V,GP,TP,5x11,5	
AE12	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
AE13	2401-000913	C-AL;22uF,20%,16V,GP,TP,5x11,5	
AE14	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
AE15	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
AE16	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
AE17	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
AE18	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
AE19	2401-000913	C-AL;22uF,20%,16V,GP,TP,5x11,5	
AE20	2401-000913	C-AL;22uF,20%,16V,GP,TP,5x11,5	
AE21	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
AE3	2401-000913	C-AL;22uF,20%,16V,GP,TP,5x11,5	
AE5	2401-000913	C-AL;22uF,20%,16V,GP,TP,5x11,5	
AE6	2401-002196	C-AL;4.7UF,20,25V,GP,TP,4X5,5MM,-	
AE7	2401-002196	C-AL;4.7UF,20,25V,GP,TP,4X5,5MM,-	
AE8	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
AE9	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
AIC2	1002-001294	IC-D/A CONVERTER;PCM1742KE,24BIT,TSSOP,1	
AIC4	1201-000163	IC-OP AMP;4560,SOP,8P,173MIL,DUAL,100V/m	
AIC5	1201-000163	IC-OP AMP;4560,SOP,8P,173MIL,DUAL,100V/m	
AL1	3301-001419	CORE-FERRITE BEAD;AB,220ohm,1.6x0.8x0.8m	
AL2	3301-001419	CORE-FERRITE BEAD;AB,220ohm,1.6x0.8x0.8m	
AQ1	0504-000128	TR-DIGITAL;-,NPN,200MW,22K/22K,SOT-23,TP	
AQ11	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
AQ12	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
AQ2	0504-000156	TR-DIGITAL;KSR2103,PNP,200MW,22K/22K,SOT	
AQ3	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
AQ4	0504-000128	TR-DIGITAL;-,NPN,200MW,22K/22K,SOT-23,TP	
AQ5	0504-000156	TR-DIGITAL;KSR2103,PNP,200MW,22K/22K,SOT	
AQ6	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
AQ7	0504-000128	TR-DIGITAL;-,NPN,200MW,22K/22K,SOT-23,TP	
AQ8	0504-000156	TR-DIGITAL;KSR2103,PNP,200MW,22K/22K,SOT	
AQ9	0501-000314	TR-SMALL SIGNAL;KSA812,PNP,150mW,SOT-23,	
AR14	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
AR15	2007-000075	R-CHIP;220ohm,5%,1/16W,DA,TP,1608	
AR16	2007-000075	R-CHIP;220ohm,5%,1/16W,DA,TP,1608	
AR17	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
AR18	2007-000075	R-CHIP;220ohm,5%,1/16W,DA,TP,1608	
AR28	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
AR29	2007-000075	R-CHIP;220ohm,5%,1/16W,DA,TP,1608	
AR30	2007-000075	R-CHIP;220ohm,5%,1/16W,DA,TP,1608	
AR31	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
AR32	2007-000075	R-CHIP;220ohm,5%,1/16W,DA,TP,1608	

Loc.No	Part No	Description ; Specification	Remark
AR33	2007-000097	R-CHIP;47Kohm,5%,1/16W,DA,TP,1608	
AR34	2007-000102	R-CHIP;100Kohm,5%,1/16W,DA,TP,1608	
AR35	2007-000097	R-CHIP;47Kohm,5%,1/16W,DA,TP,1608	
AR36	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
AR37	2007-000097	R-CHIP;47Kohm,5%,1/16W,DA,TP,1608	
AR38	2007-000102	R-CHIP;100Kohm,5%,1/16W,DA,TP,1608	
AR39	2007-000097	R-CHIP;47Kohm,5%,1/16W,DA,TP,1608	
AR40	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
AR41	2007-001179	R-CHIP;8.2Kohm,5%,1/16W,DA,TP,1608	
AR42	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
AR43	2007-000092	R-CHIP;15Kohm,5%,1/16W,DA,TP,1608	
AR44	2007-000097	R-CHIP;47Kohm,5%,1/16W,DA,TP,1608	
AR45	2007-000097	R-CHIP;47Kohm,5%,1/16W,DA,TP,1608	
AR46	2007-001179	R-CHIP;8.2Kohm,5%,1/16W,DA,TP,1608	
AR47	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
AR48	2007-000092	R-CHIP;15Kohm,5%,1/16W,DA,TP,1608	
AR49	2007-000097	R-CHIP;47Kohm,5%,1/16W,DA,TP,1608	
AR50	2007-000097	R-CHIP;47Kohm,5%,1/16W,DA,TP,1608	
AR51	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
AR52	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
AR54	2007-000102	R-CHIP;100Kohm,5%,1/16W,DA,TP,1608	
AR55	2007-000077	R-CHIP;470ohm,5%,1/16W,DA,TP,1608	
AR56	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
AR57	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
AR58	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
AR59	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
AR60	2007-001135	R-CHIP;680HM,5%,1/8W,DA,TP,3216	
CN1	3708-001696	CONNECTOR-FPC/FFC/PIC;24P,1MM,STRAIGHT,S	
CN2	3708-001695	CONNECTOR-FPC/FFC/PIC;13P,1MM,STRAIGHT,S	
CN3	3711-001018	CONNECTOR-HEADER;BOX,5P,1R,2mm,STRAIGHT,	
CN4	3708-000249	CONNECTOR-FPC/FFC/PIC;27P,1.25mm,STRAIGH	
DOC1	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
DOC2	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
DOC3	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
DOC4	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
DOE1	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
DOIC1	AH14-10004R	IC;M74HCU04,SOP,TAPE 14P	
DOIC2	3707-001052	CONNECTOR-OPTICAL;PLUG,GP1FA550TZ,6dB,2.	
DOL1	2901-001125	FILTER-EMI ON BOARD;50V,0.5A,-,220pF,7x2	
DOL2	3301-001419	CORE-FERRITE BEAD;AB,220ohm,1.6x0.8x0.8m	
DOR1	2007-000075	R-CHIP;220ohm,5%,1/16W,DA,TP,1608	
DOR2	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
DOR3	2007-000075	R-CHIP;220ohm,5%,1/16W,DA,TP,1608	
DOR4	2007-000023	R-CHIP;120OHM,5%,1/10W,DA,TP,2012	
DRC1	2203-001222	C-CERAMIC,CHIP;820pF,10%,50V,X7R,TP,1608	
DRC10	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
DRC11	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
DRC12	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
DRC13	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
DRC2	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
DRC3	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
DRC4	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
DRC5	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
DRC6	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
DRC7	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
DRC8	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
DRC9	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
DRE1	2401-002196	C-AL;4.7UF,20,25V,GP,TP,4X5,5MM,-	
DRE2	2401-002196	C-AL;4.7UF,20,25V,GP,TP,4X5,5MM,-	
DRE3	2401-002196	C-AL;4.7UF,20,25V,GP,TP,4X5,5MM,-	
DRE4	2401-001728	C-AL;10uF,20%,35V,GP,TP,5x7,5	
DRE5	2401-002095	C-AL;47uF,20%,25V,GP,TP,6.3x5,5	
DRIC1	1003-001298	IC-MOTOR DRIVER;KA3017,HQFP,48P,550MIL,1	
DRR1	2007-000034	R-CHIP;1OHM,5%,1/4W,DA,TP,3216	
DRR10	2007-000655	R-CHIP;27Kohm,5%,1/16W,DA,TP,1608	
DRR11	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
DRR12	2007-000116	R-CHIP;120ohm,5%,1/16W,DA,TP,1608	
DRR13	2007-000116	R-CHIP;120ohm,5%,1/16W,DA,TP,1608	
DRR2	2007-000034	R-CHIP;1OHM,5%,1/4W,DA,TP,3216	
DRR3	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
DRR4	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
DRR5	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
DRR6	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
DRR7	2007-000093	R-CHIP;20Kohm,5%,1/16W,DA,TP,1608	
DRR8	2007-000093	R-CHIP;20Kohm,5%,1/16W,DA,TP,1608	
DRR9	2007-000092	R-CHIP;15Kohm,5%,1/16W,DA,TP,1608	
FR1	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
FR2	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
FR3	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
FR4	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
FR5	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
FR6	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
FR7	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
JACK1	3722-001778	JACK-PIN;6P,3.2MM,NI,BLK,-	
MC1	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
MC10	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
MC11	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
MC12	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
MC13	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
MC14	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
MC15	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
MC16	2203-000626	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,160	
MC17	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
MC18	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
MC19	2203-000626	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,160	
MC2	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
MC20	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
MC22	2203-000236	C-CERAMIC,CHIP;0.1nF,5%,50V,NP0,TP,1608	
MC23	2203-000236	C-CERAMIC,CHIP;0.1nF,5%,50V,NP0,TP,1608	
MC25	2203-000236	C-CERAMIC,CHIP;0.1nF,5%,50V,NP0,TP,1608	
MC26	2203-000236	C-CERAMIC,CHIP;0.1nF,5%,50V,NP0,TP,1608	
MC27	2203-000236	C-CERAMIC,CHIP;0.1nF,5%,50V,NP0,TP,1608	
MC29	2203-000236	C-CERAMIC,CHIP;0.1nF,5%,50V,NP0,TP,1608	
MC3	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
MC5	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
MC6	2203-000626	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,160	
MC7	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
MC8	2203-000426	C-CERAMIC,CHIP;0.018nF,5%,50V,NP0,TP,160	
MC9	2203-000426	C-CERAMIC,CHIP;0.018nF,5%,50V,NP0,TP,160	
MIC1	0903-001271	IC-MICROCONTROLLER;91C829,16BIT,QFP,100P	
MIC2	1102-001090	IC-EPROM;27C081,1MX8BIT,DIP,32P,600MIL,	
MIC2B	3704-000472	SOCKET-IC;32P,DIP,SN,2.54mm	
MIC3	1103-001204	IC-EEPROM;24C021,256x8Bit,SOP,8P,150MIL,	
MIC5	0801-002143	IC-CMOS LOGIC;7S32,OR GATE,SOT-23,5P,63M	
MIC6	0801-002517	IC-CMOS LOGIC;7SET00,NAND GATE,SOP,5P,63	
MIC7	0801-002097	IC-CMOS LOGIC;7ST08,AND GATE,SOP,5P,110M	
MR1	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
MR10	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
MR11	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
MR12	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
MR13	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
MR14	2007-000109	R-CHIP;1Mohm,5%,1/16W,DA,TP,1608	
MR15	2007-000075	R-CHIP;220ohm,5%,1/16W,DA,TP,1608	
MR16	2007-000075	R-CHIP;220ohm,5%,1/16W,DA,TP,1608	
MR17	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
MR18	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
MR19	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
MR2	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
MR20	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
MR21	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
MR22	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
MR26	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	

Loc.No	Part No	Description ; Specification	Remark
MR27	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
MR28	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
MR29	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
MR3	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
MR30	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
MR31	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
MR32	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
MR33	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
MR34	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
MR35	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
MR38	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
MR39	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
MR4	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
MR40	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
MR42	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
MR43	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
MR5	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
MR6	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
MR7	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
MR8	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
MR9	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
MY1	2802-001152	RESONATOR-CERAMIC;20MHZ,0.5%,TP,5.5X3.5X	
PC1	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
PC10	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
PC11	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
PC12	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
PC13	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
PC2	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
PC3	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
PC4	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
PC5	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
PC6	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
PC7	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
PC8	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
PCB	AK41-00001A	PCB-MAIN;SV-DVD700,PHENOL,2,0,1.6T,1.6T	
PD1	0402-000309	DIODE-RECTIFIER;1SR154-400,400V,1A,SOD-1	
PE1	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
PE10	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
PE2	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
PE3	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
PE4	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
PE5	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
PE6	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
PE7	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
PE8	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
PE9	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
PIC1	1203-002178	IC-VOLTAGE REGULATOR;1563,SOP,7P,173MIL,	
PIC2	1203-002577	IC-VOLTAGE REGULATOR;MM1561J,SOP,7P,173M	
PIC3	1203-002185	IC-VOLTAGE REGULATOR;3RD13,TO-220,4P,402	
PL1	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
PL2	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
PL3	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
PL4	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
PL5	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
PL6	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
PRC1	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
PRC10	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
PRC11	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
PRC12	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
PRC13	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
PRC14	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
PRC15	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
PRC16	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
PRC17	2203-001103	C-CERAMIC,CHIP;6.8nF,10%,50V,X7R,TP,1608	
PRC18	2203-000140	C-CERAMIC,CHIP;1.5nF,10%,50V,X7R,TP,1608	
PRC19	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
PRC20	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
PRC21	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
PRC3	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
PRC4	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
PRC5	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
PRC6	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
PRC8	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
PRC9	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
PRE1	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
PRIC1	AK13-00002A	IC ASIC;S5LR010X01,-,64P,3.3/1.8 V,-0	
PRIC2	0801-002701	IC-CMOS LOGIC;74VHCT125A,BUFFER,TSSOP,14	
PRL1	3301-001419	CORE-FERRITE BEAD;AB,220ohm,1.6x0.8x0.8m	
PRL2	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
PRL3	3301-001419	CORE-FERRITE BEAD;AB,220ohm,1.6x0.8x0.8m	
PRL4	3301-001419	CORE-FERRITE BEAD;AB,220ohm,1.6x0.8x0.8m	
PRL5	3301-001419	CORE-FERRITE BEAD;AB,220ohm,1.6x0.8x0.8m	
PRQ1	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
PRR1	2007-000088	R-CHIP;7.5Kohm,5%,1/16W,DA,TP,1608	
PRR19	2007-000113	R-CHIP;33ohm,5%,1/16W,DA,TP,1608	
PRR2	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
PRR20	2007-000113	R-CHIP;33ohm,5%,1/16W,DA,TP,1608	
PRR21	2007-000113	R-CHIP;33ohm,5%,1/16W,DA,TP,1608	
PRR22	2007-000965	R-CHIP;5.1Kohm,5%,1/16W,DA,TP,1608	
PRR24	2007-000076	R-CHIP;330ohm,5%,1/16W,DA,TP,1608	
PRR25	2007-000076	R-CHIP;330ohm,5%,1/16W,DA,TP,1608	
PRR27	2007-000076	R-CHIP;330ohm,5%,1/16W,DA,TP,1608	
PRR28	2007-000076	R-CHIP;330ohm,5%,1/16W,DA,TP,1608	
PRR29	2007-000607	R-CHIP;240OHM,5%,1/10W,DA,TP,2012	
PRR3	2007-001179	R-CHIP;8.2Kohm,5%,1/16W,DA,TP,1608	
PRR31	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
PRR4	2007-000458	R-CHIP;18Kohm,5%,1/16W,DA,TP,1608	
PRR5	2007-000799	R-CHIP;360ohm,5%,1/16W,DA,TP,1608	
PRR6	2007-000098	R-CHIP;56Kohm,5%,1/16W,DA,TP,1608	
PRR7	2007-000124	R-CHIP;2.2Kohm,5%,1/16W,DA,TP,1608	
PRR8	2007-000098	R-CHIP;56Kohm,5%,1/16W,DA,TP,1608	
PRR9	2007-000799	R-CHIP;360ohm,5%,1/16W,DA,TP,1608	
RC1	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
RC10	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
RC11	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
RC12	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
RC13	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
RC14	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
RC15	2203-000560	C-CERAMIC,CHIP;220nF,+80-20%,25V,Y5V,TP,	
RC16	2203-000236	C-CERAMIC,CHIP;0.1nF,5%,50V,NP0,TP,1608	
RC17	2203-000560	C-CERAMIC,CHIP;220nF,+80-20%,25V,Y5V,TP,	
RC18	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
RC19	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
RC2	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
RC21	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
RC22	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
RC23	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
RC24	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
RC25	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
RC26	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
RC27	2203-000236	C-CERAMIC,CHIP;0.1nF,5%,50V,NP0,TP,1608	
RC28	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
RC29	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
RC3	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
RC33	2203-005065	C-CERAMIC,CHIP;1000nF,+80-20%,10V,Y5V,TP	
RC34	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-	
RC35	2203-000236	C-CERAMIC,CHIP;0.1nF,5%,50V,NP0,TP,1608	
RC36	2203-000140	C-CERAMIC,CHIP;1.5nF,10%,50V,X7R,TP,1608	
RC37	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
RC38	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
RC39	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
RC4	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	

Loc.No	Part No	Description ; Specification	Remark
RC40	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
RC41	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
RC5	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
RC6	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
RC7	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
RC8	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
RD1	0407-000116	DIODE-ARRAY;DAP202K,80V,100mA,CK2-3,SOT-	
RE1	2401-001728	C-AL;10uF,20%,35V,GP,TP,5x7,5	
RE10	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
RE11	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
RE2	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
RE3	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
RE4	2401-000913	C-AL;22uF,20%,16V,GP,TP,5x11,5	
RE5	2401-000913	C-AL;22uF,20%,16V,GP,TP,5x11,5	
RE6	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
RE7	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
RE8	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
RE9	2401-001728	C-AL;10uF,20%,35V,GP,TP,5x7,5	
RIC1	AH13-00009A	IC ASIC;KS1462B,DVD-M201/XAA,80,+5V,-4	
RL1	3301-001419	CORE-FERRITE BEAD;AB,220ohm,1.6x0.8x0.8m	
RL2	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
RQ1	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
RQ2	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
RQ3	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
RQ4	0501-000279	TR-SMALL SIGNAL;KSA1182-Y,PNP,150mW,SOT-	
RQ5	0501-000279	TR-SMALL SIGNAL;KSA1182-Y,PNP,150mW,SOT-	
RR10	2007-000312	R-CHIP;10OHM,5%,1/8W,DA,TP,3216	
RR11	2007-000077	R-CHIP;470ohm,5%,1/16W,DA,TP,1608	
RR12	2007-000102	R-CHIP;100Kohm,5%,1/16W,DA,TP,1608	
RR13	2007-000102	R-CHIP;100Kohm,5%,1/16W,DA,TP,1608	
RR14	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
RR15	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
RR16	2007-001235	R-CHIP;910Kohm,5%,1/16W,DA,TP,1608	
RR17	2007-000091	R-CHIP;12Kohm,5%,1/16W,DA,TP,1608	
RR18	2007-000655	R-CHIP;27Kohm,5%,1/16W,DA,TP,1608	
RR19	2007-000134	R-CHIP;33Kohm,5%,1/16W,DA,TP,1608	
RR22	2007-000091	R-CHIP;12Kohm,5%,1/16W,DA,TP,1608	
RR23	2007-000102	R-CHIP;100Kohm,5%,1/16W,DA,TP,1608	
RR24	2007-000102	R-CHIP;100Kohm,5%,1/16W,DA,TP,1608	
RR25	2007-000087	R-CHIP;6.8Kohm,5%,1/16W,DA,TP,1608	
RR26	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
RR27	2007-000075	R-CHIP;220ohm,5%,1/16W,DA,TP,1608	
RR28	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
RR29	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
RR3	2007-000091	R-CHIP;12Kohm,5%,1/16W,DA,TP,1608	
RR30	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
RR31	2007-000075	R-CHIP;220ohm,5%,1/16W,DA,TP,1608	
RR32	2007-000102	R-CHIP;100Kohm,5%,1/16W,DA,TP,1608	
RR33	2007-000091	R-CHIP;12Kohm,5%,1/16W,DA,TP,1608	
RR4	2007-000091	R-CHIP;12Kohm,5%,1/16W,DA,TP,1608	
RR5	2007-000091	R-CHIP;12Kohm,5%,1/16W,DA,TP,1608	
RR6	2007-001179	R-CHIP;8.2Kohm,5%,1/16W,DA,TP,1608	
RR7	2007-000082	R-CHIP;3.3Kohm,5%,1/16W,DA,TP,1608	
RR8	2007-000312	R-CHIP;10OHM,5%,1/8W,DA,TP,3216	
RR9	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
RVR1	2104-001068	VR-SMD;10Kohm,25%,1/20W,TOP	
SC1	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
SC10	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
SC11	2203-002398	C-CERAMIC,CHIP;22nF,10%,50V,X7R,TP,1608	
SC12	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
SC13	2203-002398	C-CERAMIC,CHIP;22nF,10%,50V,X7R,TP,1608	
SC14	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
SC15	2203-000491	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,1608	
SC16	2203-000491	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,1608	
SC17	2203-000372	C-CERAMIC,CHIP;15nF,10%,50V,X7R,TP,1608,	
SC18	2203-000372	C-CERAMIC,CHIP;15nF,10%,50V,X7R,TP,1608,	
SC19	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
SC2	2203-001222	C-CERAMIC,CHIP;820pF,10%,50V,X7R,TP,1608	
SC20	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
SC21	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
SC22	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
SC23	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
SC24	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
SC25	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
SC27	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
SC28	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
SC29	2203-000681	C-CERAMIC,CHIP;0.027nF,5%,50V,NP0,TP,160	
SC3	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
SC30	2203-000681	C-CERAMIC,CHIP;0.027nF,5%,50V,NP0,TP,160	
SC31	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
SC32	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
SC33	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
SC34	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
SC35	2203-000626	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,160	
SC36	2203-000626	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,160	
SC37	2203-000626	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,160	
SC38	2203-000626	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,160	
SC39	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
SC4	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
SC40	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
SC41	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
SC42	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
SC43	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
SC45	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
SC5	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
SC6	2203-001634	C-CERAMIC,CHIP;33nF,10%,50V,X7R,TP,1608,	
SC7	2203-001126	C-CERAMIC,CHIP;0.68nF,10%,50V,X7R,TP,160	
SC8	2203-000715	C-CERAMIC,CHIP;3.3nF,10%,50V,X7R,TP,1608	
SC9	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
SE1	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
SE2	2401-001728	C-AL;10uF,20%,35V,GP,TP,5x7,5	
SE3	2401-001728	C-AL;10uF,20%,35V,GP,TP,5x7,5	
SE4	2401-001728	C-AL;10uF,20%,35V,GP,TP,5x7,5	
SIC1	AH13-00006A	IC ASIC;KS1454,DVD-611/XAA,160,+3.3V,+	
SIC2	1105-001243	IC-DRAM;416C256,256KX16BIT,SOJ,40P,400	
SIC4	0801-002097	IC-CMOS LOGIC;7ST08,AND GATE,SOP,5P,110M	
SJACK	3722-001375	JACK-DIN;4P,-,NI,BLK,-	
SL1	3301-001419	CORE-FERRITE BEAD;AB,220ohm,1.6x0.8x0.8m	
SQ1	0504-000156	TR-DIGITAL;KSR2103,PNP,200MW,22K/22K,SOT	
SR1	2007-000082	R-CHIP;3.3Kohm,5%,1/16W,DA,TP,1608	
SR10	2007-000133	R-CHIP;330Kohm,5%,1/16W,DA,TP,1608	
SR11	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
SR13	2203-000140	C-CERAMIC,CHIP;1.5nF,10%,50V,X7R,TP,1608	
SR14	2007-000102	R-CHIP;100Kohm,5%,1/16W,DA,TP,1608	
SR15	2007-000091	R-CHIP;12Kohm,5%,1/16W,DA,TP,1608	
SR16	2007-001235	R-CHIP;910Kohm,5%,1/16W,DA,TP,1608	
SR17	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
SR18	2007-000092	R-CHIP;15Kohm,5%,1/16W,DA,TP,1608	
SR19	2007-000091	R-CHIP;12Kohm,5%,1/16W,DA,TP,1608	
SR2	2007-000087	R-CHIP;6.8Kohm,5%,1/16W,DA,TP,1608	
SR20	2007-000124	R-CHIP;2.2Kohm,5%,1/16W,DA,TP,1608	
SR21	2007-000124	R-CHIP;2.2Kohm,5%,1/16W,DA,TP,1608	
SR22	2007-000124	R-CHIP;2.2Kohm,5%,1/16W,DA,TP,1608	
SR23	2007-000124	R-CHIP;2.2Kohm,5%,1/16W,DA,TP,1608	
SR24	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
SR26	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
SR27	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
SR28	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
SR29	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
SR3	2007-000082	R-CHIP;3.3Kohm,5%,1/16W,DA,TP,1608	
SR30	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
SR31	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	

Loc.No	Part No	Description ; Specification	Remark
SR32	2007-000092	R-CHIP;15Kohm,5%,1/16W,DA,TP,1608	
SR33	2007-000092	R-CHIP;15Kohm,5%,1/16W,DA,TP,1608	
SR34	2007-000091	R-CHIP;12Kohm,5%,1/16W,DA,TP,1608	
SR35	2007-000093	R-CHIP;20Kohm,5%,1/16W,DA,TP,1608	
SR36	2007-000109	R-CHIP;1Mohm,5%,1/16W,DA,TP,1608	
SR38	2007-000076	R-CHIP;330ohm,5%,1/16W,DA,TP,1608	
SR39	2007-000076	R-CHIP;330ohm,5%,1/16W,DA,TP,1608	
SR4	2007-000107	R-CHIP;470Kohm,5%,1/16W,DA,TP,1608	
SR40	2007-000076	R-CHIP;330ohm,5%,1/16W,DA,TP,1608	
SR41	2007-000113	R-CHIP;33ohm,5%,1/16W,DA,TP,1608	
SR42	2007-000113	R-CHIP;33ohm,5%,1/16W,DA,TP,1608	
SR5	2007-000381	R-CHIP;13Kohm,5%,1/16W,DA,TP,1608	
SR6	2007-000799	R-CHIP;360ohm,5%,1/16W,DA,TP,1608	
SR7	2007-000097	R-CHIP;47Kohm,5%,1/16W,DA,TP,1608	
SR8	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
SR9	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
SY1	2801-000261	CRYSTAL-UNIT;33.8688MHz,50ppm,28-AAA,12p	
VC1	2203-000815	C-CERAMIC,CHIP;0.033nF,5%,50V,NP0,TP,160	
VC10	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
VC11	2203-001607	C-CERAMIC,CHIP;0.22nF,5%,50V,NP0,TP,1608	
VC12	2203-001607	C-CERAMIC,CHIP;0.22nF,5%,50V,NP0,TP,1608	
VC13	2203-001607	C-CERAMIC,CHIP;0.22nF,5%,50V,NP0,TP,1608	
VC14	2203-001607	C-CERAMIC,CHIP;0.22nF,5%,50V,NP0,TP,1608	
VC15	2203-001607	C-CERAMIC,CHIP;0.22nF,5%,50V,NP0,TP,1608	
VC16	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
VC17	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
VC18	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
VC2	2203-000815	C-CERAMIC,CHIP;0.033nF,5%,50V,NP0,TP,160	
VC3	2203-000815	C-CERAMIC,CHIP;0.033nF,5%,50V,NP0,TP,160	
VC4	2203-000815	C-CERAMIC,CHIP;0.033nF,5%,50V,NP0,TP,160	
VC5	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
VC6	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
VC7	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
VC9	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
VE1	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
VE11	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
VE13	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
VE5	2401-000913	C-AL;22uF,20%,16V,GP,TP,5x11,5	
VE7	2401-001479	C-AL;470uF,20%,10V,GP,TP,-,-	
VE9	2401-001479	C-AL;470uF,20%,10V,GP,TP,-,-	
VIC1	1201-001836	IC-VIDEO AMP;MM1567AJBE,SOP,34P,300MIL,-	
VL1	3301-001419	CORE-FERRITE BEAD;AB,220ohm,1.6x0.8x0.8m	
VL10	3301-001419	CORE-FERRITE BEAD;AB,220ohm,1.6x0.8x0.8m	
VL11	3301-001419	CORE-FERRITE BEAD;AB,220ohm,1.6x0.8x0.8m	
VL2	3301-001419	CORE-FERRITE BEAD;AB,220ohm,1.6x0.8x0.8m	
VL3	3301-001419	CORE-FERRITE BEAD;AB,220ohm,1.6x0.8x0.8m	
VL4	3301-001419	CORE-FERRITE BEAD;AB,220ohm,1.6x0.8x0.8m	
VL5	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
VL7	3301-001419	CORE-FERRITE BEAD;AB,220ohm,1.6x0.8x0.8m	
VL8	3301-001419	CORE-FERRITE BEAD;AB,220ohm,1.6x0.8x0.8m	
VL9	3301-001419	CORE-FERRITE BEAD;AB,220ohm,1.6x0.8x0.8m	
VR1	2007-001214	R-CHIP;82ohm,1%,1/16W,DA,TP,1608	
VR10	2007-001164	R-CHIP;75ohm,1%,1/16W,DA,TP,1608	
VR11	2007-000113	R-CHIP;33ohm,5%,1/16W,DA,TP,1608	
VR13	2007-001214	R-CHIP;82ohm,1%,1/16W,DA,TP,1608	
VR14	2007-001164	R-CHIP;75ohm,1%,1/16W,DA,TP,1608	
VR15	2007-000113	R-CHIP;33ohm,5%,1/16W,DA,TP,1608	
VR17	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
VR18	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
VR19	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
VR2	2007-001164	R-CHIP;75ohm,1%,1/16W,DA,TP,1608	
VR20	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
VR21	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
VR22	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
VR23	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
VR3	2007-000113	R-CHIP;33ohm,5%,1/16W,DA,TP,1608	

Loc.No	Part No	Description ; Specification	Remark
VR30	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
VR5	2007-001214	R-CHIP;82ohm,1%,1/16W,DA,TP,1608	
VR6	2007-001164	R-CHIP;75ohm,1%,1/16W,DA,TP,1608	
VR7	2007-000113	R-CHIP;33ohm,5%,1/16W,DA,TP,1608	
VR9	2007-001214	R-CHIP;82ohm,1%,1/16W,DA,TP,1608	
VZ1	0403-001083	DIODE-ZENER;UDZ9.1B,9.1V,8.85-9.23V,200m	
VZ10	0403-001083	DIODE-ZENER;UDZ9.1B,9.1V,8.85-9.23V,200m	
VZ2	0403-001083	DIODE-ZENER;UDZ9.1B,9.1V,8.85-9.23V,200m	
VZ3	0403-001083	DIODE-ZENER;UDZ9.1B,9.1V,8.85-9.23V,200m	
VZ4	0403-001083	DIODE-ZENER;UDZ9.1B,9.1V,8.85-9.23V,200m	
VZ5	0403-001083	DIODE-ZENER;UDZ9.1B,9.1V,8.85-9.23V,200m	
VZ6	0403-001083	DIODE-ZENER;UDZ9.1B,9.1V,8.85-9.23V,200m	
VZ7	0403-001083	DIODE-ZENER;UDZ9.1B,9.1V,8.85-9.23V,200m	
VZ8	0403-001083	DIODE-ZENER;UDZ9.1B,9.1V,8.85-9.23V,200m	
VZ9	0403-001083	DIODE-ZENER;UDZ9.1B,9.1V,8.85-9.23V,200m	
XC1	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-	
XC2	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
XC3	2203-000681	C-CERAMIC,CHIP;0.027nF,5%,50V,NP0,TP,160	
XC4	2203-000681	C-CERAMIC,CHIP;0.027nF,5%,50V,NP0,TP,160	
XIC1	AH14-10004R	IC;M74HCU04,SOP,TAPE 14P	
XL1	3301-001419	CORE-FERRITE BEAD;AB,220ohm,1.6x0.8x0.8m	
XL2	3301-001419	CORE-FERRITE BEAD;AB,220ohm,1.6x0.8x0.8m	
XR1	2007-000607	R-CHIP;240OHM,5%,1/10W,DA,TP,2012	
XR2	2007-000109	R-CHIP;1Mohm,5%,1/16W,DA,TP,1608	
XY1	2801-003554	CRYSTAL-UNIT;27MHz,10ppm,28-AAM,12pF,40o	
ZC1	2203-000626	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,160	
ZC10	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC100	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
ZC101	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
ZC103	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
ZC11	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC12	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC13	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC14	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC15	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC16	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC17	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC18	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC19	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC2	2203-000626	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,160	
ZC20	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC21	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC22	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC23	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC24	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC25	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC26	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC27	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC28	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC29	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC3	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC30	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC31	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC32	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC33	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC34	2203-000626	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,160	
ZC35	2203-005148	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,1608	
ZC36	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC37	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC38	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC39	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC4	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC40	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC41	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC42	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC43	2203-000626	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,160	

Loc.No	Part No	Description ; Specification	Remark
ZC44	2203-000815	C-CERAMIC,CHIP;0.033nF,5%,50V,NP0,TP,160	
ZC45	2203-000236	C-CERAMIC,CHIP;0.1nF,5%,50V,NP0,TP,1608	
ZC5	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC6	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC7	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC8	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC9	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
ZE1	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
ZE100	2401-001479	C-AL;470uF,20%,10V,GP,TP,-,-	
ZE2	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
ZE3	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
ZIC1	1204-001919	IC-DECODER;ZIVA4.1 B0,QFP,208P,28X28MM,P	
ZIC2	1105-001305	IC-DRAM;4S641632,1Mx16x4Bit,TSOP,54P,4	
ZL1	3301-001419	CORE-FERRITE BEAD;AB,220ohm,1.6x0.8x0.8m	
ZL2	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
ZL3	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
ZL4	3301-001419	CORE-FERRITE BEAD;AB,220ohm,1.6x0.8x0.8m	
ZL5	3301-001419	CORE-FERRITE BEAD;AB,220ohm,1.6x0.8x0.8m	
ZL6	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
ZL7	3301-001419	CORE-FERRITE BEAD;AB,220ohm,1.6x0.8x0.8m	
ZL8	3301-001419	CORE-FERRITE BEAD;AB,220ohm,1.6x0.8x0.8m	
ZR1	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
ZR10	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
ZR11	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
ZR15	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
ZR17	2007-007332	R-CHIP;1.18KOHM,1%,1/10W,DA,TP,2012	
ZR18	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
ZR19	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
ZR2	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
ZR20	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
ZR21	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
ZR22	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
ZR23	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
ZR24	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
ZR25	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
ZR28	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
ZR29	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
ZR3	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
ZR30	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
ZR31	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
ZR4	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
ZR5	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
ZR6	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
ZR7	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
ZR8	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
ZR9	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
701	**-**	**ASSY PCB-F/T;**	
C701	2401-000118	C-AL;1000uF,20%,10V,GP,TP,10x12.5,5	
C702	2202-000173	C-CERAMIC,MLC-AXIAL;1nF,10%,50V,Y5P,TP,1	
C703	2202-000173	C-CERAMIC,MLC-AXIAL;1nF,10%,50V,Y5P,TP,1	
C704	2401-000118	C-AL;1000uF,20%,10V,GP,TP,10x12.5,5	
C705	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C7K01	2202-000797	C-CERAMIC,MLC-AXIAL;10NF,30%,16V,Y5S,TP,	
C7K02	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C7K04	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
C7K05	2401-001915	C-AL;1uF,20%,50V,GP,TP,3x5,5	
C7K06	2202-000797	C-CERAMIC,MLC-AXIAL;10NF,30%,16V,Y5S,TP,	
C7K07	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
C7K08	2401-001915	C-AL;1uF,20%,50V,GP,TP,3x5,5	
C7K50	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C7K51	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C7K52	2401-003059	C-AL;1000UF,20%,16V,WT,TP,10X16,5	
C7K90	2401-000118	C-AL;1000uF,20%,10V,GP,TP,10x12.5,5	
CN701	3710-001145	CONNECTOR-SOCKET;20P,1R,1.5mm,STRAIGHT,S	
D701	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
D702	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
D703	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
D704	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
D705	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
D706	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
DT701	AC07-00026A	LED DISPLAY;C-327EG,X-9,70,10,7,75.95*18	
IC701	1003-001443	IC-LED DRIVER;PT6959,SOIC,28P,300MIL,-,-	
IC7K1	1201-000163	IC-OP AMP;4560,SOP,8P,173MIL,DUAL,100V/m	
L701	2701-000002	INDUCTOR-AXIAL;100uH,10%,4.2x9.8mm	
L702A	2702-000108	INDUCTOR-RADIAL;100uH,5%,6x6.4mm	
LD701	0601-000497	LED;ROUND,GRN,3.1mm,565nm	
MIC1	3722-001190	JACK-PHONE;9P/2C,6.43PI,AU,BLK,RC6701(EI	
MIC2	3722-001190	JACK-PHONE;9P/2C,6.43PI,AU,BLK,RC6701(EI	
Q701	0504-000119	TR-DIGITAL;KSR1004,NPN,300MW,47K/47K,TO-	
Q7K01	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
Q7K02	0504-000145	TR-DIGITAL;KSR2003,PNP,300MW,22K/22K,TO-	
R701	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R702	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R703	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R704	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R705	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R706	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R707	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R710	2001-000832	R-CARBON;510OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R732	2001-000837	R-CARBON;51KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R7K01	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R7K02	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R7K03	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R7K04	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R7K06	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R7K07	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R7K08	2001-000938	R-CARBON;68OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R7K09	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R7K10	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R7K11	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R7K12	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R7K13	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R7K14	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R7K15	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R7K17	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R7K18	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
RM701	AC59-60060A	MODULE REMOCON;GP1U281R,SHARP,38KHZ,-,-,	
SW701	3404-001188	SWITCH-TACT;12V,50MA,100GF,6X6X5,SPST	
SW702	3404-001188	SWITCH-TACT;12V,50MA,100GF,6X6X5,SPST	
SW703	3404-001188	SWITCH-TACT;12V,50MA,100GF,6X6X5,SPST	
SW704	3404-001188	SWITCH-TACT;12V,50MA,100GF,6X6X5,SPST	
SW705	3404-001188	SWITCH-TACT;12V,50MA,100GF,6X6X5,SPST	
SW706	3404-001188	SWITCH-TACT;12V,50MA,100GF,6X6X5,SPST	
SW708	3404-001188	SWITCH-TACT;12V,50MA,100GF,6X6X5,SPST	
SW709	3404-001188	SWITCH-TACT;12V,50MA,100GF,6X6X5,SPST	
SW710	3404-001188	SWITCH-TACT;12V,50MA,100GF,6X6X5,SPST	
SW711	3404-001188	SWITCH-TACT;12V,50MA,100GF,6X6X5,SPST	
SW712	3404-001188	SWITCH-TACT;12V,50MA,100GF,6X6X5,SPST	
SW713	3404-001188	SWITCH-TACT;12V,50MA,100GF,6X6X5,SPST	
SW714	3404-001188	SWITCH-TACT;12V,50MA,100GF,6X6X5,SPST	
SW715	3404-001188	SWITCH-TACT;12V,50MA,100GF,6X6X5,SPST	
SW716	3404-001188	SWITCH-TACT;12V,50MA,100GF,6X6X5,SPST	
SW717	3404-001188	SWITCH-TACT;12V,50MA,100GF,6X6X5,SPST	
SW718	3404-001188	SWITCH-TACT;12V,50MA,100GF,6X6X5,SPST	

MEMO